



Included accessories:

- CLA 7.1
Neck loop
- CLA 7.2
Headphone



In option :

- Additional receiver to be placed on the same base



Example with 2 receivers



*Optical input

**Analog audio or mic input

CHARACTERISTICS

- Option to connect your own headphones or hearing aids
- Stereo reception
- Optical audio input on the base*
- Analog audio or microphone input (3.5 mm jack) **
- Receiver compatible with headphones or neck loop with a 3.5mm male jack
- Easy access to the settings from the receiver:
 - Volume control (up to 125dB spl)
 - Left/Right Balance Control
 - Tone Control
- Automatic stand-by mode (once the signal to the base has ceased)
- Integrated microphone to amplify the ambient sound
- Comfortable and lightweight

TECHNICAL SPECIFICATIONS

- **2,4 GHz digital**
- Frequency response: 100 – 16 000Hz
- Operation Frequency: 2.404.5-2.479.5GHz
- Modulation Type: GFSK
- Number of Channel: 16
- Bandwidth: 5MHz
- Bit Rate of Transmitter: 1Mbps
- Antenna Type: Internal Antenna
- Charging station for two receivers (see example)
- More than 10 hours of continuous use
- Fast recharging station
 - Full charging time: 4 hours
 - The receiver recharges itself automatically once placed on the base
- Range: 100m outdoor and 25m indoor
- Weight of the receiver: 38g

BOX COMPONENTS

- Receiver
 - Neck loop CLA 7.1
 - Headphone CLA 7.2
 - Charging cradle
1. Type C power adaptor
 2. Lanyard 75cm
 3. Audio Cable (both ends with 3.5 mm stereo plug)
 4. Optical cable (Toslink) 1.8m
 5. Cord adapter RCA-to jack 3.5mm
 6. Mini optical jack

